


**SWIT**<sup>®</sup>

Model: **S-1221H**  
21.5" Broadcast Studio LCD Monitor



# User Manual

Please read this User Manual throughout before using.

## Preface

Congratulations on your purchase of this product. Please read this user manual carefully.

1. All internal technologies of this product are protected, including device, software and trademark.  
Reproduction in whole or in part without written permission is prohibited.
2. All brands and trademarks of SWIT Electronics Co., Ltd. are protected and other relative trademarks in this user manual are the property of their respective owners.
3. Due to constant effort of product development, SWIT reserves the right to make changes and improvements to the product described in this manual without prior notice.
4. The warranty period of this product is 2 years, and does not cover the following:
  - (1) Physical damage to the surface of the products, including scratches, cracks or other damage to the LCD screen or other externally exposed parts;
  - (2) Misuse, abuse or negligent operation to the product;
  - (3) The product is disassembled by anyone other than an authorized service center.

It is considered normal that the LCD bright dot defects are not to exceed three.
5. For any suggestions and requirements on this product, please contact us through phone, fax, Email, etc.

---

### **SWIT Electronics Co., Ltd.**

Address: 10 Hengtong Road, Nanjing Economic and Technological Development Zone,  
Nanjing 210038, P.R.China

Phone: +86-25-85805753

Fax: +86-25-85805296

Email: [contact@swit.cc](mailto:contact@swit.cc)

Website: <http://www.swit.cc>

## Maintenance

- **The Monitor**

1. Please keep the signal terminals and the cooling vent away from knife-edge, metal or liquid in order to avoid short-circuit and damage.
2. Please don't try to disassemble any parts of the monitor by yourself, which would probably damage the monitor and do harm to human body, and it will cause the invalidation of product warranty.
3. Please don't touch the screen with your fingers, which would probably deface the screen.
4. Please don't press the screen; the LCD is extremely exquisite and flimsy.

- **The power**

Please use the power adapter provided or recommended by the manufacturer in order to avoid damage. For a third party power adapter, please make sure the voltage range, supplied power, and polarity of power lead are fit.

Please disconnect the power cable under the following situations:

1. If you do not operate this monitor for a period of time;
2. If the power cable or power adaptor is damaged;
3. If the monitor housing is broken.

- **Working Environment**

1. Please don't lay this product on the unstable place.
2. Please don't lay this product in hot, cold or wet location.

- **Cleaning**


1. Please clean the screen with dry and downy cloth or special LCD cleanser.
2. Please do not press hard when cleaning the screen.
3. Please do not use water or other chemical cleanser to clean the screen. The chemical may damage the LCD.

## 1. Features

- ◆ **Full-HD 21.5" LCD Panel**  
1920×1080 resolution, 1000:1 contrast
- ◆ **Multiple inputs**  
3G/HD/SD-SDI, HDMI and Composite input
- ◆ **Loop through outputs**  
SDI, HDMI has loop through output
- ◆ **SDI 1080psf supported**  
Support SMPTE-RP211 format: 1080psf (30 / 29.97 / 25 / 24 / 23.98)
- ◆ **2-ch audio meter**  
Under HDSDI and HDMI, it displays 2 channels embedded audio bars with mark. The audio bar is green, and will turn yellow when audio exceeds -20dB, and turn red when exceeds -9dB.
- ◆ **SDI timecode**  
Under SDI input, it can display the SMPTE timecode (VITC1, VITC2 or LTC), which is used extensively for synchronization, and for logging and identifying material in recorded media.
- ◆ **Peaking focus assist (red/blue switch)**  
The Peaking focus assist function are available under SDI and HDMI, which is to mark the sharpest edges of the image with red or blue color, for users to check if the subjects are focused.
- ◆ **Zebra stripes**  
Zebra Stripes are used to check if the image is over exposed or not by showing black and white lines on the monitor. It is considered over exposed when luminance value exceeds 90%.
- ◆ **Blue Only**  
Under Blue Only Mode, only blue pixels are used to generate the image, because hue and saturation can be adjusted quicker and more accurately.
- ◆ **Main/Backup Power Supply**  
The monitor provides 2 DC power inputs, for main and backup power.
- ◆ **Scale Marker**  
The monitor has 16:9 native LCD panel, and supports 4:3, 13:9, 14:9, 15:9, 1.85:1 and 2.35:1 scales marker for different video producing.
- ◆ **User definable function keys**  
There are 4 function keys on the monitor front panel, which permit users to define shortcuts for the various functions.
- ◆ **User editable video title**  
User can edit a video title for the current camera, and the title will display on the top of screen.
- ◆ **3-color TALLY light**  
There's a 3-color TALLY light in the front panel of monitor, and TALLY signal is input via DB-9 connector on the rear panel.
- ◆ **Image Flip**  
Set image to rotate by 180°


## 2. Panel Instruction

### Front view



- (1) **Speaker:** For SDI/HDMI embedded audio and analog audio monitoring. (Will not work if earphone is plugged in)
- (2) **SDI1:** Press “SDI1” to switch to SDI input 1
- (3) **SDI2:** Press “SDI2” to switch to SDI input 2
- (4) **HDMI:** Press “HDMI” to switch to HDMI input
- (5) **CVBS:** Press “CVBS” to switch to CVBS input
- (6), (7), (8), (9) **F1, F2, F3, F4:** User definable function keys
- (10) **DISPLAY:** Press “Display” to display safe area, scale marker, title and the current input signal information.
- (11) **MENU:** Press to enter Menu
- (12) **ENTER:** Select and Apply  
Under menu system, revolve “ENTER” to adjust settings and press to apply; and out of menu system, directly revolve “ENTER” to adjust volume.
- (13) **BRIGHT:** Revolve “BRIGHT” to adjust brightness value from 0~100. Default value is 50.
- (14) **CONTRAST:** Revolve “CONTRAST” to adjust contrast value from 0~100. Default value is 50.
- (15) **SATURATION:** Revolve “SATURATION” to adjust saturation value from 0~100. Default value is 50.
- (16) **POWER:** Power on/off  
Connect with power cable, press the “POWER” to switch on the monitor. Press again to switch off.  
Disconnect with power cable if the monitor will not be used for a period of time.
- (17) **PHONE:** 3.5mm earphone socket, for SDI embedded audio, HDMI embedded audio monitoring.
- (18) **Desktop Stand Feet**
- (19) **TALLY Light:** Red, Green and Yellow 3-color TALLY indicator

## Rear view



### (1) Battery plate Install:

V-mount or Gold mount battery plates install position, with a hole to connect the battery plate power wires to the main board inside.

(2) **DC IN 11V-17V BACK UP:** Connect with 4-pin XLR power adaptor (Pin 1: Negative, Pin 4: Positive)

(3) **DC IN 11V-17V MAIN:** Connect with 4-pin XLR power adaptor (Pin 1: Negative, Pin 4: Positive)

(4) **VESA Mount:** Standard 10×10cm VESA bracket installation

(5) **TALLY controlling port (DB-9)**

(6) **SDI-LOOP:** 3G/HD/SD-SDI loop through output (BNC connector)

When SDI-IN2 is displayed, the SDI-LOOP outputs the SDI-IN2 signal, and when SDI-IN1 or other input sources are displayed, the SDI-LOOP outputs the SDI-IN1 signal.

(7) **SDI-IN1:** 3G/HD/SD-SDI input (BNC connector)

(8) **HDMI-LOOP:** HDMI loop through output

(9) **AUDIO-IN:** Analog stereo audio input (3.5mm)

(10) **HDMI-IN:** HDMI input

(11) **SDI-IN2:** 3G/HD/SD-SDI input (BNC connector)

(12) **CVBS-IN:** Composite video input (BNC connector)

## Input formats

Input	Supported formats
CVBS	PAL / NTSC
HDMI	480i / 576i / 480p / 576p
	720p (60 / 59.94 / 50)
	1080i (60 / 59.94 / 50), 1080psf (30 / 29.97 / 25 / 24 / 23.98)
	1080p (60 / 59.94 / 50 / 30 / 29.97 / 25 / 24 / 23.98)
SDI	SMPTE-425M
	1080p (60 / 59.94 / 50)
	SMPTE-274M
	1080i (60 / 59.94 / 50)
	1080p (30 / 29.97 / 25 / 24 / 23.98)
	SMPTE-RP211
	1080psf (30 / 29.97 / 25 / 24 / 23.98)
	SMPTE-296M
	720p (60 / 59.94 / 50)
	SMPTE-125M
	480i (59.94)
	ITU-R BT.656
	576i (50)

### 3. Menu Operation

- (1) Press "MENU" and it will display menu system
- (2) Revolve "ENTER" to select an item. The selected item will be highlighted display.
- (3) Press "ENTER" to enter the selected item.
- (4) Under menu system, press "MENU" to back to previous menu.  
\*The menu will automatically save and quit if it remains idle.

#### 3.1 PICTURE submenu

The PICTURE submenu includes:

- (1) **CONTRAST**: 0-100 value adjustment
- (2) **BRIGHTNESS**: 0-100 value adjustment
- (3) **HUE**: 0-100 value adjustment  
(Only available under CVBS NTSC input)
- (4) **SATURATION**: 0-100 value adjustment
- (5) **SHARPNESS**: 0-100 value adjustment
- (6) **BACKLIGHT**: 0-100 value adjustment

PICTURE		
PICTURE	CONTRAST	50
SYSTEM	BRIGHTNESS	50
OSD	HUE	50
TITLE	SATURATION	50
DISPLAY	SHARPNESS	50
F KEY	BACKLIGHT	75
COLOR		
	: ADJ	: OK
		: EXIT

#### 3.2 SYSTEM submenu

The SYSTEM submenu includes:

- (1) **RATIO**: Aspect ratio "16:9" / "4:3" selection
- (2) **SCAN**: "UNDERSCAN" / "OVERSCAN" / "NATIVE" selection
- (3) **ZOOM**: "OFF", "ZOOM1" and "ZOOM2" selection
- (4) **FLIP**: Select "ON" to flip the picture by 180°.
- (5) **RESET**: Select "YES" to recover all to factory setting.

SYSTEM		
PICTURE	RATIO	16:9
SYSTEM	SCAN	UNDERSCAN
OSD	ZOOM	OFF
TITLE	FLIP	OFF
DISPLAY	RESET	YES
F KEY		
COLOR		
	: ADJ	: OK
		: EXIT

#### 3.3 OSD submenu

The OSD submenu includes:

- (1) **LANGUAGE**: Menu language selection
- (2) **H-POSITION**: Menu horizontal position (0-100) adjustment, real-time preview and default value: 50.
- (3) **V-POSITION**: Menu vertical position (0-100) adjustment, real-time preview and default value: 50.
- (4) **DURATION**: Menu timeout setting (5-60)  
Set a time (in seconds) in which the menu will automatically quit if remains idle. Default: 15.

OSD		
PICTURE	LANGUAGE	ENGLISH
SYSTEM	H-POSITION	50
OSD	V-POSITION	50
TITLE	DURATION	15
DISPLAY		
F KEY		
COLOR		
	: ADJ	: OK
		: EXIT

#### 3.4 TITLE submenu

Revolve "ENTER" button to select the letters, and press "ENTER" to input. Select SPACE to input space and DEL to delete the left letter. Max 10 letters are supported.

After setting, press "MENU", the system will save data to current user and quit menu. The menu will automatically save and quit if it remains idle.

TITLE		
PICTURE	0	1
SYSTEM	2	3
OSD	4	5
TITLE	6	7
DISPLAY	8	9
F KEY	A	B
COLOR	C	D
	E	F
	G	H
	I	J
	K	L
	M	N
	O	P
	Q	R
	S	T
	U	V
	W	X
	Y	Z
	SPACE	DEL
	TITLE: CAM■1	
	: ADJ	: OK
		: EXIT

### 3.5 DISPLAY submenu

The DISPLAY submenu is to select the items to be displayed on screen when "DISPLAY" button is pressed. Revolve "ENTER" to turn on/off the items:

- (1) **INFO:** Including Input format, aspect ratio, underscan/overscan, zoom status
- (2) **TITLE:** User edited title
- (3) **MARKER SEL:** Select the scale marker from 4:3, 13:9, 14:9, 15:9, 1.85:1, 2.35:1 and OFF
- (4) **SAFE AREA:** Select the safe area scale from 80%, 85%, 90%, 95% and OFF.
- (5) **MARKER CLR:** Select the color of markers from WHITE, RED, GREEN, BLUE, BLACK and GRAY.

DISPLAY		
PICTURE	◀	ON ▶
SYSTEM	◀	ON ▶
OSD	◀	4:3 ▶
TITLE	◀	80% ▶
<b>DISPLAY</b>	◀	WHITE ▶
F KEY		
COLOR		
	[ :ADJ]	[OK :OK]
		[ :EXIT]

### 3.6 F KEY submenu

The F KEY Settings Submenu is to define Function Key F1, F2, F3 and F4. The available function items are:

- 01- **RATIO:** Aspect ratio 16:9 / 4:3 switch
- 02- **SCAN:** Underscan / Overscan switch
- 03- **ZOOM:** Picture Zoom-in
- 04- **B/W:** Color / Black & white switch
- 05- **BLUE ONLY:** Blue only mode switch on/off
- 06- **ZEBRA:** Zebra over exposure switch on/off
- 07- **TIMECODE:** SDI timecode display switch on/off
- 08- **AUDIO BAR:** Audio meter display switch on/off
- 09- **FOCUS:** Peaking focus assist switch on/off
- 10- **FLIP:** Image flip
- 11- **COLOR TEMP:** Adjust color temperature
- 12- **KEY LED:** Keyboard backlight switch on/off

F KEY		
PICTURE	◀	01-RATIO ▶
SYSTEM	◀	02-SCAN ▶
OSD	◀	03-ZOOM ▶
TITLE	◀	04-B/W ▶
DISPLAY		
<b>F KEY</b>		
COLOR		
	[ :ADJ]	[OK :OK]
		[ :EXIT]

### 3.7 COLOR submenu

The color submenu is to change the color temperature settings. User can select color temperature as 6500K, 5600K, 9300K, or define color temperature by RGB GAIN and RGB BIAS.

- (1) **COLOR TEMP:** 6500K, 5600K, 9300K, USER1, USER2, USER3
- (2) **R GAIN:** 0-255 value adjustment
- (3) **G GAIN:** 0-255 value adjustment
- (4) **B GAIN:** 0-255 value adjustment
- (5) **R BIAS:** 0-255 value adjustment
- (6) **G BIAS:** 0-255 value adjustment
- (7) **B BIAS:** 0-255 value adjustment

Remark: RGB GAIN and RGB BIAS settings are only available when "Color temp" is set as USER1/2/3

COLOR		
PICTURE	◀	6500K ▶
SYSTEM	R GAIN	128
OSD	G GAIN	128
TITLE	B GAIN	128
DISPLAY	R BIAS	128
<b>F KEY</b>	G BIAS	128
COLOR	B BIAS	128
	[ :ADJ]	[OK :OK]
		[ :EXIT]

## 4. TALLY Light Operation


The front TALLY light can display 3 colors: RED, GREEN and YELLOW. The TALLY light controlling port is the DB-9 socket at the rear panel, and terminal description is as follows:

Terminal	1	2	3	4	5	6	7	8	9
Description		Y	G	R					GND

The RED light is on when connecting the terminal "R" with "GND", and goes out when disconnecting.

The GREEN light is on when connecting the terminal "G" with "GND", and goes out when disconnecting.

The YELLOW light is on when connecting the terminal "Y" with "GND", and goes out when disconnecting.




## 5. Specifications

LCD Performance	
Size	21.5 inches
Display area	477×268mm
Resolution	1920×RGB×1080
Aspect ratio	16:9 (4:3 adjustable)
Brightness	250cd/m <sup>2</sup>
Contrast	1000:1
Color	16.77 million colors
Viewing angle	Horizontal: 178° Vertical: 178°
Video Format	
CVBS	NTSC / PAL
SDI	SMPTE-425M 1080p (60 / 59.94 / 50)
	SMPTE-274M 1080i (60 / 59.94 / 50)
	1080p (30 / 29.97 / 25 / 24 / 23.98)
	SMPTE-RP211 1080psf (30 / 29.97 / 25 / 24 / 23.98)
	SMPTE-296M 720p (60 / 59.94 / 50)
	SMPTE-125M 480i (59.94)
	ITU-R BT.656 576i (50)
HDMI	480I / 576I / 480P / 576P
	720p (60 / 59.94 / 50)
	1080i (60 / 59.94 / 50), 1080psf (30 / 29.97 / 25 / 24 / 23.98)
	1080p (60 / 59.94 / 50 / 30 / 29.97 / 25 / 24 / 23.98)
General	
Working voltage	DC / battery 11V-17V
Power consumption	≤40W
Working temperature	0°C～+40°C
Working humidity	10%～90%
Storage temperature	- 15°C～ + 60°C
Storage humidity	10%～90%
Dimensions (w/o stand)	525×358×47mm
Net weight (w/o stand)	6.69kg


## 6. Packing List

Monitor	×1
Desktop stand	×2
User manual	×1
4-pin XLR AC-DC Power adaptor	×1
Power cable	×1


## 7. Optional Accessories





V-mount Plate




Gold Mount Plate




Magnetic LCD protective organic glass



VESA desktop stand




19-inch Rack install bracket




## 8. Installation Dimension


### 8.1 With Desktop Stand Feet (in mm)



### 8.2 With VESA Desktop Stand (in mm)



### 8.3 With 19-inch Rack Bracket (in mm)



**SWIT**<sup>®</sup>